



Circular Current Loop as a Magnetic Dipole

Unlocking the hidden mathematical symmetry between electrostatics and magnetism.



Field on the Axis Revisited

To understand how a loop behaves at a distance, we must start with the **exact magnetic field** formula for an axial point P.



Exact Field
(Valid for all x)

Steady current Loop radius

$$B = \frac{\mu_0 I R^2}{2(x^2 + R^2)^{3/2}}$$

Distance along axis

The Far-Field Dipole Analogy

Apply Far-Field Boundary Condition

$x \gg R$ (Drop the R^2 term in the denominator)

$$B \approx \frac{\mu_0 I R^2}{2x^3}$$

Introduce Area to force symmetry

$$\text{Area } A = \pi R^2 \Rightarrow R^2 = \frac{A}{\pi}$$

$$B = \frac{\mu_0 I A}{2\pi x^3}$$

Match the familiar Electrostatic formatting ($1/4\pi\epsilon_0$)

Multiply numerator and denominator by 2

$$B = \frac{\mu_0}{4\pi} \frac{2(IA)}{x^3}$$

The expression (IA) is grouped intentionally. It forms the core of our new concept.



**You've Learned the Theory.
Let's Test Them Now.**

$$E=mc^2$$



Turn theory into marks with **unlimited MCQs, smart analysis, and focused revision.**

Practice Now



At prep.topall.app

Key Highlights

- » Free Study Material, Videos & Infographics
- » Push Your Limits with Level-Based Challenges
- » Climb the Leaderboard Among Fellow Aspirants
- » Practice Unlimited MCQs for NEET & JEE
- » Get Clear Explanations, Not Just Marks
- » Track Your Performance Smarter



Defining the Magnetic Moment (m)

Definition

Equation Chip

$$m = IA$$

N-Turns Chip

For a tightly wound coil with N turns:


$$m = NIA$$

Exam Detail

Dimensions: $[A][L^2]$ | **SI Unit:** $A\ m^2$

Direction

Magnetic moment is a vector quantity. Its direction is strictly determined by the Right-Hand Thumb Rule.



The Translation Matrix: Electricity vs. Magnetism

Electrostatics		Magnetism	
Electrostatic Dipole (p)	Source	Magnetic Dipole (m)	
$1/\epsilon_0$	Constant	μ_0	
$E = \frac{1}{4\pi\epsilon_0} \frac{2p}{x^3}$	Axial Field	$B = \frac{\mu_0}{4\pi} \frac{2m}{x^3}$	
$E \approx \frac{1}{4\pi\epsilon_0} \frac{p}{x^3}$	Equatorial Field	$B \approx \frac{\mu_0}{4\pi} \frac{m}{x^3}$	



THE CRITICAL ASYMMETRY


An electric dipole is built from two distinct elementary charges (monopoles). In magnetism, the current loop is the elementary element. Magnetic monopoles are not known to exist.

Summary & Exam Blueprint

Key Takeaways



1. **The Macro View:** At large distances ($x \gg R$), a circular current loop behaves mathematically exactly like an electric dipole.



2. **The Core Formula:** The equivalent magnetic moment of a current loop is $m = NIA$. Its direction follows the right-hand thumb rule.



3. **The Fundamental Difference:** While electric field lines originate and terminate on isolated charges (monopoles), magnetic field lines form continuous closed loops. Isolated magnetic monopoles do not exist.



You've Learned the Theory.

Now Let's Test It.

Reading notes gets you knowledge.

Practicing MCQs gets you marks.

That's exactly what TopAll Pro is built for.

Try TopAll Pro Now

What TopAll Pro Does Differently

-  **Stuck? Snap it. Solve it. — Doubts AI**
Photo → step-by-step solution in seconds, 24/7
-  **Your AI Coach finds your blind spots**
Concept-level weakness detection — not just chapter-level
-  **4.5 Lakh+ questions. Never run out.**
13× more content than any other prep app in India
-  **Build your own test in 60 seconds**
Pick a chapter, set difficulty — AI does the rest instantly.
-  **AI Recommendation that helps you improve**
AI Recommendation Analysis your Tests and tell you where you need to improve.



Practice the moment you finish studying
Jump in while the concept is still fresh in your head

4.5L+
MCQs

1.5L+
Students

AI Powered
In-Depth Analysis