


The Moving Coil Galvanometer

From first principles to practical instrumentation: mastering the anatomy, physics, and mathematical sensitivities of the MCG.




[NEET/JEE Physics]

[Magnetic Torque]

[Circuit Instrumentation]


Why We Need a Measuring Device

The Abstract



We know that currents and moving charges interact with magnetic fields (Lorentz force). But these forces and fields are invisible.

The Practical



How do we definitively claim a circuit has a 1.5 A current or a 1.2 V drop? We need a device that translates invisible electrical flow into a visible, calibrated mechanical response.

Enter the Moving Coil Galvanometer (MCG). An instrument designed to detect and measure micro-currents by harnessing magnetic torque.

Anatomy of the Galvanometer

The Coil

A multi-turn wire coil free to rotate about a fixed axis.

Soft Iron Core

A cylindrical core placed inside the coil. Crucial function: It makes the magnetic field radial and increases field strength.

Concave Pole Pieces


Magnets shaped to ensure the field lines point radially across the coil's rotational path.

Pointer & Scale

Translates the microscopic angular twist into a readable linear scale.

The Spring (Sp)

A delicate hairspring that provides a mechanical counter-torque when the coil twists.





**You've Learned the Theory.
Let's Test Them Now.**

$$E=mc^2$$



Turn theory into marks with **unlimited MCQs, smart analysis, and focused revision.**


Practice Now



At prep.topall.app

Key Highlights

- » Free Study Material, Videos & Infographics
- » Push Your Limits with Level-Based Challenges
- » Climb the Leaderboard Among Fellow Aspirants
- » Practice Unlimited MCQs for NEET & JEE
- » Get Clear Explanations, Not Just Marks
- » Track Your Performance Smarter



The Physics of Deflection: A Torque Tug-of-War



**Driving Force
(Magnetic)**

$$\tau = NIAB$$

- Current (I) flows through N turns of area A in magnetic field B .

Radial Field Magic: Because the field is radial, the angle is always 90° , making $\sin\theta = 1$ constantly.



**Restoring Force
(Mechanical)**



$$\tau = k\varphi$$

- The spring twists by angle φ , resisting with a torsional constant k .

The Equilibrium Point

The pointer stops moving when the torques **perfectly balance**.

$$k\varphi = NIAB$$

Current Sensitivity & Optimization

Current Sensitivity = Deflection
per unit current (φ/I)

Chip N:

↑ **Increase Turns** (High impact,
but increases resistance).

Chip A:

↑ **Increase Area**
(Limited by device size).

$$\frac{\varphi}{I} = \frac{NAB}{k}$$

Chip B:

↑ **Increase Magnetic Field**
(Achieved via soft iron core).

Chip k:

↓ **Decrease Torsion Constant**
(Use a softer, more delicate spring).


⚠ The Voltage Sensitivity Trap (Exam Favorite)

Increasing turns ($N \rightarrow 2N$) doubles Current Sensitivity.
But it also doubles the wire's resistance ($R \rightarrow 2R$).
Therefore,
Voltage Sensitivity ($\varphi/V = NAB/kR$) remains unchanged.

Hacking the MCG: Conversion to an Ammeter



The basic MCG is too sensitive (maxes out at micro-amps μA) and its high resistance would alter the circuit's overall current.



Shunt (r_s):
A very small resistance placed in parallel.

Mechanism:
It acts as a bypass lane, absorbing almost all the current so the delicate coil isn't fried.

Effective Resistance of Ammeter:
$$R_{eq} = \frac{R_G \times r_s}{R_G + r_s} \approx r_s \text{ (since } R_G \gg r_s \text{)}.$$

The instrument now has negligible resistance.

Exam Mastery: Key Takeaways

Core Equilibrium

$$k\phi = NIAB$$

Always remember the soft iron core guarantees the radial field, so $\sin\theta$ is always 1.

Sensitivities

Current: $I_s = NAB/k$

Voltage: $V_s = NAB/kR$

The N Paradox

Doubling turns (N) doubles current sensitivity, but leaves voltage sensitivity completely unchanged due to proportional resistance increase.

Instrument Conversion

To Ammeter: Connect tiny Shunt (r_s) in Parallel. (Ideal resistance $\rightarrow 0$).

To Voltmeter: Connect large Resistance (R) in Series. (Ideal resistance $\rightarrow \infty$).



You've Learned the Theory.

Now Let's Test It.

Reading notes gets you knowledge.

Practicing MCQs gets you marks.

That's exactly what TopAll Pro is built for.

Try TopAll Pro Now

What TopAll Pro Does Differently

-  **Stuck? Snap it. Solve it. — Doubts AI**
Photo → step-by-step solution in seconds, 24/7
-  **Your AI Coach finds your blind spots**
Concept-level weakness detection — not just chapter-level
-  **4.5 Lakh+ questions. Never run out.**
13× more content than any other prep app in India
-  **Build your own test in 60 seconds**
Pick a chapter, set difficulty — AI does the rest instantly.
-  **AI Recommendation that helps you improve**
AI Recommendation Analysis your Tests and tell you where you need to improve.



Practice the moment you finish studying
Jump in while the concept is still fresh in your head

4.5L+
MCQs

1.5L+
Students

AI Powered
In-Depth Analysis